



22238

PS200 12 V Power Supply with Charging Regulator but without Battery



Image Not Available

For International Shipment

Overview

The 22238 is the regulator and housing of the PS200 Smart Power Supply without the internal battery. The 22238 is a charge controller that manages amperage and voltage for safe, optimized battery charging from your solar panel or ac power source. It also measures various input, output, and status

parameters to enable you to closely monitor the battery during charging and use. An external battery cable is included.

This product is designed for international shipment where the shipping costs (and regulations) associated with batteries are formidable. You must obtain a 7-Ahr Yuasa cell locally.

Detailed Description

The 22238 orders the regulator and housing of the PS200 without the internal battery; an external battery cable is also included. This product is designed for international shipment where the shipping costs (and regulations) associated with shipping batteries are formidable. The customer must obtain a 7 Ahr Yuasa cell locally.

The 22238 is a micro-controller-based smart charger with two-step constant voltage charging and temperature compensation that optimize battery charging and increases the battery's life. Two input terminals allow simultaneous connection of two charging sources. A maximum power point tracking algorithm is incorporated for solar inputs to maximize available solar charging resources. RS-232 and SDI-12 terminals

allow the 22238 to convey charging parameters to a datalogger.

The 22238 has several safety features intended to protect the charging source, battery, charger, and load devices. Both the SOLAR – G and CHARGE – CHARGE input terminals incorporate hardware current limits and polarity reversal protection.

A fail-safe, self-resettable thermal fuse protects the CHARGE – CHARGE inputs in the event of a catastrophic AC/AC or AC/DC charging source failure. Another self-resettable thermal fuse protects the 12 V output terminals of the charger in the event of an output load fault.

The 22238 also has battery reversal protection, and includes ESD and surge protection on all of its inputs and outputs.

Specifications

Operational Temperature -40° to +60°C (VRLA battery manufacturers state that “heat kills batteries” and recommend operating batteries at ≤ 50°C.)

CHARGE - CHARGE Terminals (AC or DC Source)

AC	18 to 24 V RMS (with 1.2 A RMS maximum)
DC	16 to 40 Vdc (with 1.1 A DC maximum)

SOLAR Terminals (Solar Panel or Other DC Source)

-NOTE- Battery voltages below 8.7 V may result in less than 3.0 A current limit because of fold-back current limit.

Input Voltage Range	15 to 40 Vdc
Maximum Charging Current	4.0 Adc typical (3.2 to 4.9 Adc depending on individual charger)

Quiescent Current

No Charge Source Present	300 µA maximum
No Battery Connected	2 mA maximum

Battery Charging

-NOTE- Two-step temperature-compensated constant-voltage charging for valve-regulated lead-acid batteries; cycle and float charging voltage parameters are programmable with the default values listed.

CYCLE Charging	$V_{batt}(T) = 14.70 \text{ V} - (24 \text{ mV}) \times (T - 25^\circ\text{C})$
----------------	---

FLOAT Charging $V_{batt}(T) = 13.65 \text{ V} - (18 \text{ mV}) \times (T - 25^\circ\text{C})$

Accuracy ±1% (on charging voltage over -40° to +60°C)

Power Out (+12 Terminals)

Voltage	Unregulated 12 V from battery
4 A Self-Resettable Thermal Fuse Hold Current Limit	<ul style="list-style-type: none"> › > 4 A (< 20°C) › 4.0 A (20°C) › 3.1 A (50°C) › 2.7 A (60°C)

Measurements

<i>-NOTE-</i>	<i>Over -40° to +60°C range</i>
Average Battery Voltage	±(1% of reading + 15 mV)
Average Battery/Load Current Regulator Input Voltage	±(2% of reading + 2 mA) Impulse type changes in current may have an average current error of ±(10% of reading + 2 mA).
Solar	±(1% of reading - 0.25 V)/-(1% of reading + 1 V) 1.0 V negative offset is worst-case due to reversal protection diode on input; typical diode drop is 0.35 V.
Continuous	±(1% of reading - 0.5 V)/-(1% of reading + 2 V) 2.0 V negative offset is worst-case due to two series diodes in AC full-bridge. Typical diode drops are 0.35 each for 0.7 V total.
Charger Temperature	± 2°C

For comprehensive details, visit: www.campbellsci.com.au/pn22238 



Campbell Scientific Australia | 411 Bayswater Road | Garbutt, QLD 4814 | +61 (0)7 4401 7700 | www.campbellsci.com.au
 AUSTRALIA | BRAZIL | CANADA | CHINA | COSTA RICA | FRANCE | GERMANY | THAILAND | SOUTH AFRICA | SPAIN | UK | USA

© 2018 Campbell Scientific, Inc. | 06/15/2018