

VWAnalyzer

Vibrating Wire Analyzer



Ultimate Vibrating Wire Field Reader

For installations, system maintenance, and manual measurements



Overview

The Vibrating Wire Analyzer (VWAnalyzer) is the most innovative vibrating wire field reader available. The VWAnalyzer is field ready to quickly measure your sensor, save your data, and communicate the results with custom PDF reports and spreadsheet output. VWAnalyzer measurements are geolocated with an integrated GPS, allowing the device to verify locations and direct you to your sensors. The VWAnalyzer uses spectral-analysis technology (VSPECT®) to provide the best vibrating wire measurement possible while filtering out environmental and electrical noise. The large color display offers you an easy-to-view graphical presentation of the data.

Learn about our patented VSPECT spectral-analysis technology at our [VSPECT Essentials web resource](#).

The dynamic vibrating wire measurement technique is protected under U.S. Patent No. 8,671,758, and the vibrating wire spectral-analysis technology (VSPECT) is protected under U.S. Patent No. 7,779,690.

Benefits and Features

- Custom PDF reports
- Measurement confidence with graphical display and VSPECT technology
- Full-color screen and easy-to-use menus
- Integrated GPS to record sensor location
- Ability to read any vibrating wire sensor
- Sensor library containing common vibrating wire sensors
- Quick transfer of PDF and CSV files with a USB connection



I Detailed Description

The VWAnalyzer uses patented VSPECT technology for the most reliable vibrating wire measurements available. The VWAnalyzer converts measurements to engineering units, generates a printable PDF report, and saves a CSV summary file. The graphical display allows confirmation of sensor output and operation. VSPECT technology eliminates disruptive noise interference and provides sensor diagnostics for the best measurement possible. VSPECT noise immunity allows gauges that are otherwise unreadable to be evaluated with confidence.

A project file maintains site/sensor information for 40 unique sites with 22 sensors per site. Site/sensor locations are geolocated, allowing the internal GPS to guide a user directly to a sensor location. Site/sensor and user information can be created or edited on the device or with a computer using the free VwProjects software.

Note: The VWAnalyzer can be connected to a computer and is treated like an external memory device (flash memory drive) to transfer data.

What is a VSPECT measurement?

VSPECT provides the best vibrating wire measurement available. A sensor frequency is easily identified while filtering out environmental and electrical noise that affect the quality of other vibrating wire readers. VSPECT provides measurement diagnostics to understand sensor response and installation quality, and identify incorrect wiring or damaged sensors.

Output and Diagnostics

Sensor Frequency (Hz)

Frequency is a measured value.

Basic measurement from a vibrating wire sensor. The frequency can be converted into engineering units (for example: pressure, displacement) and is the largest measured amplitude signal within the frequency sweep.

Sensor Amplitude (mV RMS)

Diagnostic values describe the quality of the frequency measurement.

Signal strength from the vibrating wire sensor. Amplitude varies and is affected by the sensor type, excitation strength (adjustable), and sensor cable length, the main variables that determine the error between measured air temperature and the actual air temperature. An energy balance equation is then used to calculate what the actual temperature should be to an accuracy of $\pm 0.6^{\circ}\text{C}$.

Signal-to-Noise Ratio (unitless)

Diagnostic values describe the quality of the frequency measurement.

Sensor signal amplitude divided by the largest noise amplitude within the sweep frequency. A low signal-to-noise ratio indicates a weak sensor signal or a noisy environment.

Noise Frequency (Hz)

Diagnostic values describe the quality of the frequency measurement.

Largest amplitude noise signal within the frequency sweep

Decay Ratio

Diagnostic values describe the quality of the frequency measurement.

Signal attenuation (how quickly the signal strength decreases)

Thermistor/RTD Resistance (Ω)

Resistance is a measured value.

Measurement used to calculate sensor temperature and correct for thermal effects. The VWAnalyzer measures the vibrating wire sensor temperature (when present); thermal and barometric corrections require post processing.



Specifications

■ Memory	<ul style="list-style-type: none">➤ NOTE: Non-volatile memory stores data, reports, and project files. When memory is full, new data overwrite the oldest data. Users need to delete/transfer files when memory is full.➤ 1,700 site/sensor measurements (most recent)➤ 40 unique sites, 22 sensors per site➤ 240 single measurements (most recent)➤ 16,500 continuous measurements (most recent)➤ 80 MB USB memory (PDF, CSV, VWA, and other files)
-----------------	---

■ GPS	±5 m (16.4 ft) typical (±1 ms time sync)
■ Channel Count	1 channel (vibrating wire and thermistor reading)
■ Enclosure	IP62
■ Battery Type/Life	5 AA (1.5 V) 20 hours continuous use
■ Operating Temperature Range	-20° to +70°C
■ Compliance	CE, RoHS
■ USB Mini B	Direct connect to PC (supplies power to retrieve data)
■ Warranty	One year against defects in materials and workmanship
■ Dimensions	200 x 100 x 58 mm (7.9 x 3.9 x 2.3 in.)
■ Weight	0.34 kg (0.75 lb)

Measurements – Vibrating Wire

■ Vibrating Wire Frequency Range	300 to 6500 Hz
■ Resolution	0.001 Hz RMS
■ Accuracy	±0.005% of reading
■ Excitation	2 V, 5 V, 12 V (user-selectable)

■ Method	VSPECT - U.S. Patent No. 7,779,690
■ Measurement Interval Range	1 s to 15 min (continuous reading mode only)
■ Speed	1 s (fastest)

Measurements – Thermistor

■ Resolution	0.01 Ω RMS
■ Accuracy	±0.15% of reading

