



Electrical specifications are valid over a -40 to +70 °C, non-condensing environment, unless otherwise specified. Extended electrical specifications (noted as XT in specifications) are valid over a -55 to +85 °C non-condensing environment. Recalibration is recommended every three years. Critical specifications and system configuration should be confirmed with Campbell Scientific before purchase.

System specifications .....	1
Physical specifications .....	1
Power requirements .....	1
Power output specifications .....	2
Analog measurement specifications .....	3
Pulse measurement specifications .....	5
Digital input/output specifications .....	5
Communications specifications .....	6
Standards compliance specifications .....	7
Warranty .....	7
Terminal functions .....	8

## System specifications

**Processor:** Renesas RX63N (32-bit with hardware FPU, running at 100 MHz)

### Memory:

- Total onboard: 128 MB of flash + 4 MB battery-backed SRAM
  - Data storage: 4 MB SRAM + 72 MB flash (extended data storage automatically used for auto-allocated Data Tables not being written to a card)
  - CPU drive: 30 MB flash
  - OS load: 8 MB flash
  - Settings: 1 MB flash
  - Reserved (not accessible): 10 MB flash
- Data storage expansion: Removable microSD flash memory, up to 16 GB

### NOTE:

CR6 dataloggers with serial numbers less than 7502 have the following memory specifications:

**CPU Drive / Programs:** 1 MB flash

**USR Drive / Data:** 4 MB SRAM (battery backed)

**Program Execution Period:** 1 ms to 1 day

### Real-Time Clock:

- Battery backed while external power is disconnected
- **Resolution:** 1 ms
- **Accuracy:** ±3 min. per year, optional GPS correction to ±10 µs; 5.7 ppm

**Wiring Panel Temperature:** Measured using a thermistor, located on the analog board.

## Physical specifications

**Dimensions:** 21.0 x 10.2 x 5.6 cm (8.3 x 4.0 x 2.2 in); additional clearance required for cables, wires, and antennas.

### Weight/Mass:

- CR6: 0.42 kg (0.92 lb)
- CR6-WIFI: 0.50 kg (1.10 lb)
- CR6-RF451/RF452: 0.52 kg (1.15 lb)
- CR6-RF407/412/422/427: 0.51 kg (1.13 lb)

**Case Material:** High-impact-resistant polycarbonate and UV-resistant TPE, recycle code 7

**Dust Plug Material:** UV-resistant TPE

## Power requirements

**Protection:** Power inputs are protected against surge, over-voltage, over-current, and reverse power. IEC 61000-4 Class 4 level.

### CHG Terminal Characteristics (CHG+ and CHG-):

- Input from Power converter or solar panel
- \*ES1 PS2 energy sources only
- 16 to 32 VDC

- Input current limit @ 12 VDC:
  - Hold limit 1.2 A @ 20 °C

#### Battery Terminal Characteristics (BAT+ and BAT-):

- Voltage input 12 VDC only
- Hold Current limit 2.5 A @ 20 °C

#### NOTE:

\*Energy Source Class 1 (ES1) and Power Source Class 2 (PS2), as defined in Clauses 5 and 7 of IEC/AS/NZS 62368-1:2022.

#### External Batteries:

- Float charge on BAT terminal
- 12 VDC
- Valve-regulated, lead-acid (VRLA)
- 2 to 24 Ah battery typical

**Vehicle Power Connection:** When primary power is pulled from the vehicle power system, a second power supply OR charge regulator may be required to overcome the voltage drop at vehicle start-up.

**USB Power:** Functions that will be active with USB 5 VDC include sending programs, adjusting data logger settings, and making some measurements. If USB is the only power source, then the CS I/O port and the 12V and SW12 terminals will not be operational.

**Internal Lithium Battery:** AA, 2.4 Ah, 3.6 VDC (Tadiran TL 5903/S) for battery-backed SRAM and clock. 3-year life with no external power source.

#### Average Current Drain:

Assumes 12 VDC on BAT terminals — add 2 mA if using CHG terminals.

- **Idle:** <1 mA
- **Active 1 Hz Scan:** 3 mA
- **Active 20 Hz Scan:** 67 mA
- **Serial (RS-232/RS-485):** Active + 25 mA
- **Ethernet Power Requirements:**
  - **Ethernet 1 Minute:** Active + 1 mA
  - **Ethernet Idle:** Active + 4 mA
  - **Ethernet Link:** Active + 47 mA

#### Wi-Fi Additional Current Contribution at 12 VDC:

Mode	Wi-Fi Option
Client Mode	7 mA idle, 70 mA communicating
Access Point Mode	62 mA idle, 70 mA communicating
Sleep	<1 mA

#### RF Average Additional Current Contribution at 12 VDC:

	-RF407, -RF412, -RF427	-RF422	-RF451/RF452
Transmit	< 80 mA	20 mA	650 mA, maximum
Idle On	12 mA	9.5 mA	15 mA, maximum

	-RF407, -RF412, -RF427	-RF422	-RF451/RF452
Idle 0.5 s Power Mode	4 mA	3.5 mA	NA
Idle 1 s Power Mode	3 mA	2 mA	NA
Idle 4 s Power Mode	1.5 mA	1.5 mA	NA

## Power output specifications

### System power out limits (when powered with 12 VDC)

Temperature (°C)	Current limit <sup>1</sup> (A)
-40°	3.88
0°	2.98
20°	2.50
50°	1.80
70°	1.35
85°	1.00
<sup>1</sup> Limited by self-resetting thermal fuse	

### 12 V and SW12 V power output terminals

12V, SW12-1, and SW12-2: Provide unregulated 12 VDC power with voltage equal to the Power Input supply voltage. These are disabled when operating on USB power only.

SW12 current limits	
Temperature (°C)	Current limit <sup>1</sup> (mA)
-40°	1600
0°	1290
20°	1100
50°	830
70°	640
85°	500
<sup>1</sup> Thermal fuse hold current.	

### U and C as power output

- C Terminals:
  - **Output Resistance ( $R_O$ ):** 150  $\Omega$
  - **5 V Logic Level Drive Capacity:** 10 mA @ 3.5 VDC
  - **3.3 V Logic Level Drive Capacity:** 10 mA @ 1.8 VDC

- U Terminals:

	U odd terminals	U even terminals
Voltage Excitation Max Current @ $\pm 2500$ mV	$\pm 25$ mA	$\pm 25$ mA
Current Excitation Max Current	$\pm 2500$ $\mu$ A	$\pm 2500$ $\mu$ A
5 V Logic Level Output Resistance ( $R_o$ )	75 $\Omega$	150 $\Omega$
5 V Logic Level Max Current @ 3.5 V	20 mA	10 mA
3.3 V Logic Level Output Resistance ( $R_o$ )	73 $\Omega$	145 $\Omega$
3.3 V Logic Level Max Current @ 1.85 V	20 mA	10 mA
U odd terminals: U1, U3, U5, U7, U9, U11. U even terminals: U2, U4, U6, U8, U10, U12		

## CS I/O pin 1

5 V Logic Level Max Current: 200 mA

## Voltage and current excitation specifications

A 12-bit DAC produces voltage and current excitation. When used for resistance measurement, excitation is active only during measurement.

### Voltage excitation

**Terminals:** U1 - U12

**Range:**  $\pm 2500$  mV

**Resolution:** 0.6 mV

**Voltage Excitation Absolute Accuracy:**

- 0 to 40 °C:  $\pm(0.1\%$  of setting + 1.2 mV)
- -40 to 70 °C:  $\pm(0.1\%$  of setting + 1.5 mV)
- -55 to 85 °C (XT):  $\pm(0.1\%$  of setting + 1.6 mV)

**Maximum Source or Sink Current:**  $\pm 25$  mA

### Current excitation

**Terminals:** U1 - U12

**Range:**  $\pm 2.5$  mA

**Resolution:** 0.6  $\mu$ A

**Current Excitation Absolute Accuracy:**

- 0 to 40 °C:  $\pm(0.11\%$  of setting + 2.0  $\mu$ A)
- -40 to 70 °C:  $\pm(0.12\%$  of setting + 2.5  $\mu$ A)
- -55 to 85 °C (XT):  $\pm(0.13\%$  of setting + 3.0  $\mu$ A)

**Compliance Voltage:**  $\pm 5$  V

## Analog measurement specifications

12 universal (U) terminals individually configurable for voltage, thermocouple, thermistor, current loop, ratiometric, static

vibrating wire, and period average measurements, using a 24-bit ADC. One channel at a time is measured.

## Voltage measurements

**Terminals:**

- **Differential Configuration (H/L):** U1/U2- U11/U12
- **Single-Ended Configuration:** U1 – U12

**Input Resistance:** 20 G $\Omega$  typical

**Input Voltage Limits:**  $\pm 5$  V

**Sustained Input Voltage without Damage:**  $\pm 20$  VDC

**DC Common Mode Rejection:**

- >120 dB with input reversal
- $\geq 86$  dB without input reversal

**Normal Mode Rejection:** > 70 dB @ 60 Hz

**Input Current @ 25 °C:**  $\pm 2$  nA typical

**Filter First Notch Frequency ( $f_{N1}$ ) Range:** 5 Hz to 93 kHz (user specified)

**Analog Range and Resolution:**

		Differential with input reversal		Single-ended and differential without input reversal	
Notch frequency ( $f_{N1}$ ) (Hz)	Range <sup>1</sup> (mV)	RMS ( $\mu$ V)	Bits <sup>2</sup>	RMS ( $\mu$ V)	Bits <sup>2</sup>
15000	$\pm 5000$	20.0	19	30.0	18
	$\pm 1000$	4.0	19	5.5	18
	$\pm 200$	1.6	18	1.8	17
50/60 <sup>3</sup>	$\pm 5000$	1.2	23	5.0	20
	$\pm 1000$	0.24	23	1.1	20
	$\pm 200$	0.10	22	0.24	20
5	$\pm 5000$	0.60	24	4.9	20
	$\pm 1000$	0.12	24	1.0	20
	$\pm 200$	0.05	23	0.22	20

<sup>1</sup> Range overhead of ~5% on all ranges guarantees that full-scale values will not cause over range

<sup>2</sup> Typical effective resolution (ER) in bits; computed from ratio of full-scale range to RMS resolution.

<sup>3</sup> 50/60 corresponds to rejection of 50 and 60 Hz ac power mains noise.

**Accuracy** (does not include sensor or measurement noise):

- 0 to 40 °C:  $\pm(0.04\%$  of measurement + offset)
- -40 to 70 °C:  $\pm(0.06\%$  of measurement + offset)
- -55 to 85 °C (XT):  $\pm(0.08\%$  of measurement + offset)

## Voltage Measurement Accuracy Offsets:

Range (mV)	Typical offset (μV RMS)	
	Differential with input reversal	Single-ended or differential without input reversal
±5000	±10	±40
±1000	±5	±12
±200	±2	±6

**Measurement Settling Time:** 20 μs to 600 ms; 500 μs default

## Multiplexed Measurement Time:

Measurement time = INT(multiplexed measurement time • (reps+1) + 2ms

	Differential with input reversal	Single-ended or differential without input reversal
Example fN1 <sup>1</sup> (Hz)	Time <sup>2</sup> (ms)	Time <sup>2</sup> (ms)
15000	2.8	1.4
60	36	18.1
50	42.07	21.3
5	402.7	201.4
<sup>1</sup> Notch frequency (1/integration time).		
<sup>2</sup> Default settling time of 500 μs used.		

## Resistance measurement specifications

The data logger makes ratiometric-resistance measurements for four- and six-wire full-bridge circuits and two-, three-, and four-wire half-bridge circuits using voltage excitation or for direct resistance measurements using current excitation. Excitation polarity reversal is available to minimize dc error.

### Accuracy:

Assumes input reversal for differential measurements

**RevDiff** and excitation reversal **RevEx** for excitation voltage <1000 mV and excitation current < 1 mA. Does not include bridge resistor errors or sensor and measurement noise.

- 0 to 40 °C: ±(0.02% of voltage measurement + offset)
- -40 to 70 °C: ±(0.025% of voltage measurement + offset)
- -55 to 85 °C (XT): ±(0.03% of voltage measurement + offset)

**Terminals:** U1-U12

**Accuracy:** ±(0.01% of measurement + resolution), where resolution is 0.13 μs divided by the number of cycles to be measured

### Ranges:

- Minimum signal centered around specified period average threshold.

- Maximum signal centered around data logger ground.
- Maximum frequency = 1/(2 \* [minimum pulse width]) for 50% duty cycle signals

Gain code option	Voltage gain	Minimum peak to peak signal (mV)	Maximum peak to peak signal (V)	Minimum pulse width (μs)	Maximum frequency (kHz)
0	1	500	10	2.5	200
1	2.5	50	2	10	50
2	12.5	10	2	62	8
3	64	2	2	100	5

## Static vibrating wire measurement specifications

Up to 6 static vibrating wire measurements without thermistor measurements, or up to 3 static vibrating wire measurements with thermistor measurements. A U terminal pair both excites and measures vibrating wire transducers. Logarithmic sine-wave-frequency excitation is adjustable up to ±6 V (12 V peak-to-peak), programmable from 100 Hz to 6.5 kHz, then followed by frequency domain measurements, one at a time.

**Terminals:** U1 - U12

**Input Resistance:** 4.75 kΩ

**Measurement Type:** Differential voltage

**Range:** ±200 mV

**Accuracy:** ±0.013% of reading

**Resolution:** 0.001 Hz RMS

**Measurement Speed** (vibrating wire and thermistor combined): < 1 s

## Thermistor measurement specifications

6 U terminal pairs can be configured to measure two-wire thermistors directly using an on-board 5 kΩ resistor to complete the bridge. The U terminal pair both excites and measures the thermistor.

**Terminals:** U1 - U12

**Input Resistance:** 5 kΩ ±0.1%, 10 ppm/°C completion resistor

**Measurement Type:** Single-ended voltage

**Range:** ±5000 mV

**Resolution:** 0.001 Ω RMS

**Accuracy:** ±0.25% of reading

## Current-loop measurement specifications

The data logger makes current-loop measurements by measuring across a current-sense resistor associated with the RS-485 resistive ground terminal.

**NOTE:**

Resistance to ground input for non-isolated 0-20 mA and 4-20 mA current loop measurements is available in CR6 data loggers with serial numbers 7502 and greater.

**Terminal:** RG

**Maximum Input Voltage:**  $\pm 16$  V

**Resistance to Ground:** 101  $\Omega$

**Current Measurement Shunt Resistance:** 10  $\Omega$

**Maximum Current Measurement Range:**  $\pm 80$  mA

**Absolute Maximum Current:**  $\pm 160$  mA

**Resolution:**  $\leq 20$  nA

**Accuracy:**

- 0 to 40 °C:  $\pm 0.14\%$  of reading
- -40 to 70 °C:  $\pm 0.26\%$  of reading

## Pulse measurement specifications

The data logger can measure switch closure or high-frequency pulse signals on C and U terminals. Terminals are configured as pairs with options for pull-up or pull-down. Even-numbered U terminals can be configured as low-level AC inputs. Each terminal has its own independent 24-bit counter. Terminal pairs are U1 and U2, U3 and U4, through U11 and U12.

**NOTE:**

Conflicts can occur when a control port pair is used for different instructions (`TimerInput()`, `PulseCount()`, `SDI12Recorder()`, `WaitDigTrig()`). For example, if C1 is used for `SDI12Recorder()`, C2 cannot be used for `TimerInput()`, `PulseCount()`, or `WaitDigTrig()`.

**Pulse Event:** Transition from logic low to logic high.

Terminal Pair Configuration	Logic Low	Logic High
5 V	$\leq 1.5$ V	$\geq 3.5$ V
3.3 V	$\leq 0.8$ V	$\geq 2.0$ V

**Sustained Input Voltage without Damage:**  $\pm 20$  VDC

**Maximum Counts Per Scan:**  $2^{24}$

**Input Resistance:** 5 k $\Omega$

**Accuracy:**  $\pm (0.02\% \text{ of reading} + 1/\text{scan})$

### Low-level AC input

**Terminals:** U2, U4, U6, U8, U10, U12

**NOTE:**

When an even numbered U terminal (for example, U2) is used for low-level AC pulse counting, its paired odd numbered terminal (U1 in this example) can be used only for switch-closure.

**DC-offset rejection:** Internal AC coupling eliminates DC-offset voltages up to  $\pm 0.05$  VDC

**Input Hysteresis:** 12 mV at 1 Hz

**Low-Level AC Pulse Input Ranges for U Terminals:**

Sine wave (mV RMS)	Range (Hz)
20	1.0 to 20
200	0.5 to 200
2000	0.3 to 10,000
5000	0.3 to 20,000

### Switch closure input

**Terminals:** C1-C4, U1-U12

**Resistance:** Configurable in terminal pairs with 100 k $\Omega$  pull-up or pull-down

**Maximum Input Frequency:** 150 Hz

**Minimum Switch Closed Time:** 5 ms

**Minimum Switch Open Time:** 6 ms

**Maximum Bounce Time:** 1 ms open without being counted

**Software Debounce Time:** 3.3 ms

### High-frequency input

**Terminals:** C1-C4, U1-U12

**Resistance:** Configurable in terminal pairs with 100 k $\Omega$  pull-up or pull-down

**Typical Wave Form:** 5 or 3.3 VDC square wave

**Maximum Input Frequency:** 1 MHz

## Digital input/output specifications

Terminals configurable for digital input and output (I/O) including status high/low, pulse width modulation, external interrupt, edge timing, switch closure pulse counting, high-frequency pulse counting, plus UART<sup>1</sup>, RS-232<sup>2</sup>, RS-422<sup>3</sup>, RS-485<sup>4</sup>, SDM<sup>5</sup>, SDI-12<sup>6</sup>, I2C<sup>7</sup>, and SPI<sup>8</sup> serial-communications

<sup>1</sup>Universal Asynchronous Receiver/Transmitter for asynchronous serial communications.

<sup>2</sup>Recommended Standard 232. A loose standard defining how two computing devices can communicate with each other. The implementation of RS-232 in Campbell Scientific data loggers to computer communications is quite rigid, but transparent to most users. Features in the data logger that implement RS-232 communications with smart sensors are flexible.

<sup>3</sup>Communications protocol similar to RS-485. Most RS-422 sensors will work with RS-485 protocol.

<sup>4</sup>Recommended Standard 485. A standard defining how two computing devices can communicate with each other.

<sup>5</sup>Synchronous Device for Measurement. A processor-based peripheral device or sensor that communicates with the data logger via hardware over a short distance using a protocol proprietary to Campbell Scientific.

<sup>6</sup>Serial Data Interface at 1200 baud. Communications protocol for transferring data between the data logger and SDI-12 compatible smart sensors.

<sup>7</sup>Inter-Integrated Circuit is a multi-controller, multi-peripheral, packet switched, single-ended, serial computer bus.

<sup>8</sup>Serial Peripheral Interface - a clocked synchronous interface, used for short distance communications, generally between embedded devices.



functions. Terminals are configurable in pairs for 5 V or 3.3 V logic for some functions.

**NOTE:**

Conflicts can occur when a control port pair is used for different instructions (`TimerInput()`, `PulseCount()`, `SDI12Recorder()`, `WaitDigTrig()`). For example, if C1 is used for `SDI12Recorder()`, C2 cannot be used for `TimerInput()`, `PulseCount()`, or `WaitDigTrig()`.

**Sustained Logic Input Voltage without Damage:** ±20 VDC

**Logic Levels and Drive Current:**

Terminal pair configuration	5 V source	3.3 V source
Logic low	≤ 1.5 V	≤ 0.8 V
Logic high	≥ 3.5 V	≥ 2.5 V
C1 - C4	10 mA @ 3.5V	10 mA @ 1.85V
U odd	20 mA @ 3.5V	20 mA @ 1.85V
U even	10 mA @ 3.5V	10 mA @ 1.85V

**Edge timing**

**Terminals:** C1-C4, U1-U12

**Maximum Input Frequency:** ≤ 1 kHz

**Resolution:** 520 ns

**Edge counting**

**Terminals:** C1-C4, U1-U12

**Maximum Input Frequency:** ≤ 2.2 kHz

**Quadrature input**

**Terminals:** C1-C4 and U1-U12 can be configured as digital pairs to monitor the two sensing channels of an encoder.

**Maximum Frequency:** 2.5 kHz

**Resolution:** 31.25 µs or 32 kHz

**Minimum Pulse Width:** 10 µs

**Pulse-width modulation**

**Modulation Voltage:** Logic high

**Maximum Period:** 128 seconds

**Resolution:**

- **0 to ≤ 5 ms:** 1/12 MHz or 83.33 ns
- **> 5 to ≤ 300 ms:** 187.62 kHz or 5.33 µs
- **> 300 ms:** 1/32 kHz or 31.25 µs

**Communications specifications**

**Ethernet Port:** RJ45 jack, 10/100Base Mbps, full and half duplex, Auto-MDIX, magnetic isolation, and TVS surge protection.

**Internet Protocols:** Ethernet, PPP, RNDIS, ICMP/Ping, Auto-IP (APIPA), IPv4, IPv6, UDP, TCP, TLS (v1.2), DNS, DHCP, SLAAC, Telnet, HTTP(S), SFTP, FTP(S), POP3/TLS, NTP, SMTP/TLS, SNMPv3, CS I/O IP, MQTT

**Additional Protocols:** CPI, PakBus, PakBus Encryption, SDM, SDI-12, Modbus RTU / ASCII / TCP, DNP3 outstation, custom user definable over serial, NTCIP, NMEA 0183, I2C, SPI

**USB Device:** Micro-B device for computer connectivity

**CS I/O:** 9-pin D-sub connector to interface with Campbell Scientific CS I/O peripherals.

**0 – 5 V Serial** (U1 to U12, C1 to C4): Eight independent TX/RX pairs

**SDI-12** (C1, C3, U1, U3, U5, U7, U9, U11): Eight independent SDI-12 compliant terminals are individually configured and meet SDI-12 Standard v 1.4.

**RS-485** (C1 to C4): Two half duplex

**RS-422** (C1 to C4): One full duplex or two half duplex

**RS-232/CPI:** Single RJ45 module port that can operate in one of two modes: CPI or RS-232. CPI interfaces with Campbell Scientific CDM measurement peripherals and sensors. RS-232 connects, with an adapter cable, to computer, sensor, or communications devices serially.

**CPI:** One CPI bus. Up to 1 Mbps data rate. Synchronization of devices to 5 µs. Total cable length up to 610 m (2000 ft). Up to 20 devices. CPI is a proprietary interface for communications between Campbell Scientific data loggers and Campbell Scientific CDM peripheral devices. It consists of a physical layer definition and a data protocol.

**Antenna Connection:**

- Wi-Fi
- SS 900 MHz
- 2.4 GHz

**Wireless:** Wi-Fi, VHF, UHF, spread spectrum, ELOS

**Hardwired:** Multi-drop, short haul, RS-232, fiber optic

**Satellite:** GOES, Argos, Inmarsat Hughes, Iridium

**Wi-Fi option specifications**

**WLAN** (Wi-Fi) (CR6-WIFI only)

**Maximum Possible Over-the-Air Data Rates:** <11 Mbps over 802.11b, <54 Mbps over 802.11g, <72 Mbps over 802.11n

**Operating Frequency:** 2.4 GHz, 20 MHz bandwidth

**Antenna Connector:** Reverse Polarity SMA (RPSMA)

**Antenna** (shipped with data logger): Unity gain (0 dBd), 1/2 wave whip, omnidirectional. Features an articulating knuckle joint that can be oriented vertically or at right angles

**Supported Technologies:** 802.11 b/g/n, WPA/WPA2-Personal, WPA/WPA2-Enterprise Security, WEP

**Client Mode:** WPA/WPA2-Personal and Enterprise, WEP

**Access Point Mode:** WPA2-Personal

**Receive Sensitivity:** -97 dBm

**RF radio option specifications**

**Antenna Terminal:** Reverse Polarity SMA (RPSMA)

## Radio Type

- **RF407, RF412, RF427, and RF451/RF452:** Frequency-Hopping Spread-Spectrum (FHSS)
- **RF407, RF412, and RF427:** Frequency-Hopping Spread-Spectrum (FHSS)
- **RF422:** SRD860 Radio with Listen Before Talk (LBT) and Automatic Frequency Agility (AFA)

## Frequency

- **RF407:** 902 to 928 MHz (US, Canada)
- **RF412:** 915 to 928 MHz (Australia, New Zealand)
- **RF422:** 863 to 870 MHz (Europe, Middle East, and Africa)
- **RF427:** 902 to 907.5 MHz/915 to 928 MHz (Brazil)
- **RF451/RF452:** 902 to 928 MHz

## Transmit Power Output (software selectable)

- **RF407 and RF412:** 5 to 250 mW
- **RF422:** 2 to 25 mW
- **RF427:** 5 to 250 mW
- **RF451/RF452:** 10 mW to 1,000 mW

## Channel Capacity

- **RF407:** Eight 25-channel hop sequences sharing 64 available channels.
- **RF412:** Eight 25-channel hop sequences sharing 31 available channels.
- **RF422:** Ten 30-channel hop sequences (default), software configurable to meet local regulations; 10 sequences for reducing interference through channel hop.
- **RF427:** Eight 25-channel hop sequences sharing 43 available channels.
- **RF451/RF452:** 50 to 112 user-selectable channels for a given network.

## Receive Sensitivity

- **RF407, RF412, and RF427:** -101 dBm
- **RF422:** -106 dBm
- **RF451/RF452:**
  - -108 dBm at 115.2 kbps for  $10^{-4}$  BER
  - -103 dBm at 153.6 kbps for  $10^{-4}$  BER

## RF Data Rate

- **RF407, RF412, and RF427:** 200 kbps
- **RF422:** 10 kbps
- **RF451/RF452:** 115.2 or 153.6 kbps

## Maximum nodes in network

- **RF407, RF412, and RF427:** 50
- **RF422:** 20
- **RF451/RF452:** 4 repeaters

## Standards compliance specifications

View compliance and conformity documents at [www.campbellsci.com/cr6](http://www.campbellsci.com/cr6).

**Shock and Vibration:** MIL-STD 810G methods 516.6 and 514.6

**Protection:** IP50

## EMI and ESD protection:

- **Immunity:** Meets or exceeds following standards:
  - **ESD:** per IEC 61000-4-2;  $\pm 15$  kV air,  $\pm 8$  kV contact discharge
  - **Radiated RF:** per IEC 61000-4-3; 10 V/m, 80-1000 MHz
  - **EFT:** per IEC 61000-4-4; 4 kV power, 4 kV I/O
  - **Surge:** per IEC 61000-4-5; 4 kV power, 4kV I/O
  - **Conducted RF:** per IEC 61000-4-6; 10 V power, 10 V I/O
- Emissions and immunity performance criteria available on request.

## RF407 Option

- United States FCC Part 15.247: MCQ-XB900HP
- Industry Canada (IC): 1846A-XB900HP
- Mexico IF: RCPDIXB15-0672-A1

## RF412 Option

- ACMA RCM
- United States FCC Part 15.247:
- MCQ-XB900HP
- Industry Canada (IC): 1846A-XB900HP

**RF422 Option:** View EU Declaration of Conformity at [www.campbellsci.com/cr6](http://www.campbellsci.com/cr6).

**RF427 Option:** Brazil ANATEL standards in Resolution No. 506: 08335-17-10644. View the RF427 Brazilian Certificate of Conformity at [www.campbellsci.com/cr6](http://www.campbellsci.com/cr6).

## RF452 Option:

- United States FCC ID: KNYMM3
- Industry Canada (IC): 2329B-MM3

## RF451 Option:

- United States FCC ID: KNYAMM0921TT
- Industry Canada (IC): 2329B-AMM0921TT

## WIFI Option

- United States FCC ID: XF6-RS9113SB
- Industry Canada (IC): 8407A-RS9113SB

### NOTE:

The user is responsible for emissions if changing the antenna type or increasing the gain.

## Warranty

**Standard:** Three years against defects in materials and workmanship.

**Extended (optional):** An additional four years, bringing the total to seven years.

## Terminal functions

### Analog input terminal functions

	U1	U2	U3	U4	U5	U6	U7	U8	U9	U10	U11	U12	RG
Single-Ended Voltage	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	
Differential Voltage	H	L	H	L	H	L	H	L	H	L	H	L	
Ratiometric/Bridge	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	
Vibrating Wire (Static, VSPECT®)	✓		✓		✓		✓		✓		✓		
Vibrating Wire with Thermistor	✓				✓				✓				
Thermistor	✓		✓		✓		✓		✓		✓		
Thermocouple	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	
Current Loop													✓
Period Average	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	

### Pulse counting terminal functions

	U1	U2	U3	U4	U5	U6	U7	U8	U9	U10	U11	U12	C1-C4
Switch-Closure	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
High Frequency	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Low-level AC		✓		✓		✓		✓		✓		✓	

### Analog output terminal functions

	U1-U12
Switched Voltage Excitation	✓
Switched Current Excitation	✓

### Voltage output terminal functions

	U1-U12 <sup>1</sup>	C1-C4 <sup>1</sup>	12V	SW12-1	SW12-2
3.3 VDC	✓	✓			
5 VDC	✓	✓			
12 VDC			✓	✓	✓

<sup>1</sup>C and U terminal voltage levels are configured in pairs. By default, digital ports are output 5V. They can be set to 3.3V using the [PortPairConfig](#) instruction in CRBasic.



Communications terminal functions																	
	U1	U2	U3	U4	U5	U6	U7	U8	U9	U10	U11	U12	C1	C2	C3	C4	RS-232/CPI
SDI-12	✓		✓		✓		✓		✓		✓		✓		✓		
GPS Time Sync	PPS	Rx											Tx	Rx	Tx	Rx	
TTL <sub>1</sub> 0-5 V	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	
LVTTL <sup>1</sup> 0-3.3 V	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	Tx	Rx	
RS-232													Tx	Rx	Tx	Rx	✓
RS-485 (Half Duplex)													A-	B+	A-	B+	
RS-485 (Full Duplex)													Tx-	Tx+	Rx-	Rx+	
I2C	SCL	SDA	SCL	SDA	SCL	SDA	SCL	SDA	SCL	SDA	SCL	SDA	SCL	SDA	SCL	SDA	
SPI	SCLK	COPI	CIPO		SCLK	COPI	CIPO		SCLKI	COPI	CIPO		SCLK	COPI	CIPO		
SDM	Data	Clk	Enabl		Data	Clk	Enabl		Data	Clk	Enabl		Data	Clk	Enabl		
CPI/ CDM																	✓
<sup>1</sup> TTL and LVTTL are configured with the CommsMode option of the <a href="#">SerialOpen</a> instruction in CRBasic.																	

Digital I/O terminal functions		
	U1-U12	C1-C4
General I/O	✓	✓
Pulse-Width Modulation Output	✓	✓
Timer Input	✓	✓
Interrupt	✓	✓
Quadrature	✓	✓

# Global Sales and Support Network

A worldwide network to help meet your needs



## Campbell Scientific Regional Offices

### Australia

**Location:** Garbutt, QLD Australia  
**Phone:** 61.7.4401.7700  
**Email:** [info@campbellsci.com.au](mailto:info@campbellsci.com.au)  
**Website:** [www.campbellsci.com.au](http://www.campbellsci.com.au)

### Brazil

**Location:** São Paulo, SP Brazil  
**Phone:** 11.3732.3399  
**Email:** [vendas@campbellsci.com.br](mailto:vendas@campbellsci.com.br)  
**Website:** [www.campbellsci.com.br](http://www.campbellsci.com.br)

### Canada

**Location:** Edmonton, AB Canada  
**Phone:** 780.454.2505  
**Email:** [dataloggers@campbellsci.ca](mailto:dataloggers@campbellsci.ca)  
**Website:** [www.campbellsci.ca](http://www.campbellsci.ca)

### China

**Location:** Beijing, P. R. China  
**Phone:** 86.10.6561.0080  
**Email:** [info@campbellsci.com.cn](mailto:info@campbellsci.com.cn)  
**Website:** [www.campbellsci.com.cn](http://www.campbellsci.com.cn)

### Costa Rica

**Location:** San Pedro, Costa Rica  
**Phone:** 506.2280.1564  
**Email:** [info@campbellsci.cc](mailto:info@campbellsci.cc)  
**Website:** [www.campbellsci.cc](http://www.campbellsci.cc)

### France

**Location:** Montrouge, France  
**Phone:** 0033.0.1.56.45.15.20  
**Email:** [info@campbellsci.fr](mailto:info@campbellsci.fr)  
**Website:** [www.campbellsci.fr](http://www.campbellsci.fr)

### Germany

**Location:** Bremen, Germany  
**Phone:** 49.0.421.460974.0  
**Email:** [info@campbellsci.de](mailto:info@campbellsci.de)  
**Website:** [www.campbellsci.de](http://www.campbellsci.de)

### India

**Location:** New Delhi, DL India  
**Phone:** 91.11.46500481.482  
**Email:** [info@campbellsci.in](mailto:info@campbellsci.in)  
**Website:** [www.campbellsci.in](http://www.campbellsci.in)

### Japan

**Location:** Kawagishi, Toda City, Japan  
**Phone:** 048.400.5001  
**Email:** [jp-info@campbellsci.com](mailto:jp-info@campbellsci.com)  
**Website:** [www.campbellsci.co.jp](http://www.campbellsci.co.jp)

### South Africa

**Location:** Stellenbosch, South Africa  
**Phone:** 27.21.8809960  
**Email:** [sales@campbellsci.co.za](mailto:sales@campbellsci.co.za)  
**Website:** [www.campbellsci.co.za](http://www.campbellsci.co.za)

### Spain

**Location:** Barcelona, Spain  
**Phone:** 34.93.2323938  
**Email:** [info@campbellsci.es](mailto:info@campbellsci.es)  
**Website:** [www.campbellsci.es](http://www.campbellsci.es)

### Thailand

**Location:** Bangkok, Thailand  
**Phone:** 66.2.719.3399  
**Email:** [info@campbellsci.asia](mailto:info@campbellsci.asia)  
**Website:** [www.campbellsci.asia](http://www.campbellsci.asia)

### UK

**Location:** Shephed, Loughborough, UK  
**Phone:** 44.0.1509.601141  
**Email:** [sales@campbellsci.co.uk](mailto:sales@campbellsci.co.uk)  
**Website:** [www.campbellsci.co.uk](http://www.campbellsci.co.uk)

### USA

**Location:** Logan, UT USA  
**Phone:** 435.227.9120  
**Email:** [info@campbellsci.com](mailto:info@campbellsci.com)  
**Website:** [www.campbellsci.com](http://www.campbellsci.com)